





















































PB SERIES

PB SERIES	PEDESTAL ONLY LOW TO HIGH	PB SERIES	PEDESTAL + BC-PH5 (BOTTOM SLOPE CORRECTOR) LOW TO HIGH	PB SERIES	PEDESTAL + BC-PH5 + KIT 5 (FIXED JOIST HOLDER) LOW TO HIGH	PB SERIES	PEDESTAL + BC-PH5 + KIT 2 (ADJUSTABLE JOIST HOLDER) LOW TO HIGH
		(OR) PEDS+KIT5 FIXED JOIST HOLDERS+BC-PH5 SLOPE CORRECTORS				USE LONG PLUG AND PIN TO ATTACH KIT-2 (+ 7/16")	
 PB 01	1-1/8" to 1-5/8"	 PB 01 + BC-PH5	1-5/8" to 2-1/8"	 PB 01 + BC-PH5 + KIT 5	1-5/8" to 2-1/8"	 PB 01 + BC-PH5 + KIT 2	2-1/16" to 2-5/8"
 PB 1	1-5/8" to 2-3/8"	 PB 1 + BC-PH5	2-1/8" to 2-7/8"	 PB 1 + BC-PH5 + KIT 5	2-1/8" to 2-7/8"	 PB 1 + BC-PH5 + KIT 2	2-5/8" to 3-5/16"
 PB 2	2-3/8" to 3-1/2"	 PB 2 + BC-PH5	2-7/8" to 4"	 PB 2 + BC-PH5 + KIT 5	2-7/8" to 4"	 PB 2 + BC-PH5 + KIT 2	3-5/16" to 4-7/16"
 PB 3	3-1/2" to 5-3/4"	 PB 3 + BC-PH5	4" to 6-1/4"	 PB 3 + BC-PH5 + KIT 5	4" to 6-1/4"	 PB 3 + BC-PH5 + KIT 2	4-7/16" to 6-11/16"
 PB 4	5-3/4" to 9-3/4"	 PB 4 + BC-PH5	6-1/4" to 10-1/4"	 PB 4 + BC-PH5 + KIT 5	6-1/4" to 10-1/4"	 PB 4 + BC-PH5 + KIT 2	6-11/16" to 10-11/16"
 C1-B4 (COUPLER)	ADDS 3-1/4" to 4-3/4"	 -	-	 -	-	 -	-
 PB 5 (PB 3 + x1 C1)	6-7/8" to 10-1/2"	 PB 5 (PB 3 + x1 C1) + BC-PH5	7-3/8" to 11"	 PB 5 (PB 3 + x1 C1) + BC-PH5 + KIT 5	7-3/8" to 11"	 PB 5 (PB 3 + x1 C1) + BC-PH5 + KIT 2	7-13/16" to 11-7/16"
 PB 6 (PB 4 + x1 C1)	11-1/8" to 14-7/16"	 PB 6 (PB 4 + x1 C1) + BC-PH5	11-5/8" to 15"	 PB 6 (PB 4 + x1 C1) + BC-PH5 + KIT 5	11-5/8" to 15"	 PB 6 (PB 4 + x1 C1) + BC-PH5 + KIT 2	12-1/16" to 15-7/16"
 PB 7 (PB 4 + x1 C2)	14-7/16" to 19-3/16"	 PB 7 (PB 4 + x1 C2) + BC-PH5	14-15/16" to 19-11/16"	 PB 7 (PB 4 + x1 C2) + BC-PH5 + KIT 5	14-15/16" to 19-11/16"	 PB 7 (PB 4 + x1 C2) + BC-PH5 + KIT 2	15-3/8" to 20-1/8"
 PB 8 (PB 4 + x1 C1 + x1 C2)	17-13/16" to 23-7/8"	 PB 8 (PB 4 + x1 C1 + x1 C2) + BC-PH5	18-1/4" to 24-3/8"	 PB 8 (PB 4 + x1 C1 + x1 C2) + BC-PH5 + KIT 5	18-1/4" to 24-3/8"	 PB 8 (PB 4 + x1 C1 + x1 C2) + BC-PH5 + KIT 2	18-11/16" to 24-13/16"
 PB 9 (PB 4 + x2 C2)	21-1/16" to 28-5/8"	 PB 9 (PB 4 + x2 C2) + BC-PH5	21-9/16" to 29-1/8"	 PB 9 (PB 4 + x2 C2) + BC-PH5 + KIT 5	21-9/16" to 29-1/8"	 PB 9 (PB 4 + x2 C2) + BC-PH5 + KIT 2	22" to 29-9/16"
 PB 10 (PB 4 + x1 C1 + x2 C2)	24-3/8" to 33-3/8"	 PB 10 (PB 4 + x1 C1 + x2 C2) + BC-PH5	24-7/8" to 33-7/8"	 PB 10 (PB 4 + x1 C1 + x2 C2) + BC-PH5 + KIT 5	24-7/8" to 33-7/8"	 PB 10 (PB 4 + x1 C1 + x2 C2) + BC-PH5 + KIT 2	25-5/16" to 34-5/16"
 PB 11 (PB 4 + x3 C2)	27-3/4" to 38-1/8"	 PB 11 (PB 4 + x3 C2) + BC-PH5	28-3/16" to 38-5/8"	 PB 11 (PB 4 + x3 C2) + BC-PH5 + KIT 5	28-3/16" to 38-5/8"	 PB 11 (PB 4 + x3 C2) + BC-PH5 + KIT 2	28-5/8" to 39-1/16"

5-10% SLOPE: x2 BC-PH5 SLOPE CORRECTORS + x1 BC-1 + 1"

10-15% SLOPE: x3 BC-PH5 SLOPE CORRECTORS + x2 BC-1 + 2"